

EXAMPLE OF APPLICATION WITH LOAD CELL



### DESCRIPTION

- LCB transforms an analog load cell (mV/V output) into a digital one; it can also be used on existing load cells to digitize the weighing system.
- Conceived for IoT applications (Internet of Things).
- PC configuration software via micro USB port.
- Status LED of the communication interface.
- Mounting: wired or integral to the load cell body via standard ¼ GAS fitting (specific adapters for different threads are supplied on request).
- 2x M4 fixing holes for wall mounting via anchor plate (not included in the supply).
- IP67 AISI316 stainless steel box (dimensions: 97x38x82 mm including flying connectors).
- 3x IP67 M12 flying connectors included in the supply.




LCB WITH FLYING CONNECTORS

### INPUTS/OUTPUTS AND COMMUNICATION

- 1 micro USB port.
- 3 relay outputs controlled by the setpoint values or via protocols.
- 2 digital inputs: status reading via serial communication protocols.
- 1 load cell input.

### PC CONFIGURATION SOFTWARE



### MICRO USB FOR PC CONFIGURATION



### FIELD BUSES

MODBUS RTU

MODBUS/TCP

ETHERNET  
POWERLINK

EtherCAT

EtherNet/IP

IO-Link

PROFIBUS

PROFINET

CC-Link

CC-Link IE

CANopen

SERCOS  
interface

ETHERNET  
TCP/IP

### INTERFACES AND FIELDBUSES

|   | CODE          |
|---|---------------|
| <b>RS485.</b><br>Male M12 circular connector, A-coded, 5-pin.<br>Female M12 circular connector, A-coded, 5-pin.<br>Baud rate: 2400, 4800, 9600, 19200, 38400, 115200 (bit/s).   | LCBRS485      |
| <b>RS485 + analog output.</b><br>Current output: 0÷20 mA; 4÷20 mA (up to 400 Ω).<br>Voltage output: 0÷10 V; 0÷5 V (min 2 kΩ).<br>Male M12 circular connector, A-coded, 5-pin.<br>Female M12 circular connector, A-coded, 5-pin. | LCBRS485ANA   |
| <b>IO-Link.</b><br>Male M12 circular connector, A-coded, 5-pin.<br>The instrument works as <i>device</i> in a IO-Link network.  | LCBIOLINK     |
| <b>CANopen.</b><br>Male M12 circular connector, A-coded, 5-pin.<br>Female M12 circular connector, A-coded, 5-pin.<br>The instrument works as <i>slave</i> in a CANopen synchronous network.                                     | LCBCANOPEN    |
| <b>CC-Link IE.</b><br>2x female M12 circular connectors, D-coded, 4-pin.<br>The instrument works as <i>slave</i> in a CC-Link IE network.   | LCBCCLINKIE   |
| <b>CC-Link.</b><br>Male M12 circular connector, A-coded, 4-pin.<br>Female M12 circular connector, A-coded, 5-pin.<br>The instrument works as <i>Remote Device Station</i> in a CC-Link network and occupies 3 stations.         | LCBCCLINK     |
| <b>PROFIBUS DP.</b><br>Male M12 circular connector, B-coded, 5-pin.<br>Female M12 circular connector, B-coded, 5-pin.<br>The instrument works as <i>slave</i> in a Profibus-DP network.   | LCBPROFIBUS   |
| <b>Modbus/TCP.</b><br>2x female M12 circular connectors, D-coded, 4-pin.<br>The instrument works as <i>slave</i> in a Modbus/TCP network.   | LCBMODBUSTCP  |
| <b>Ethernet TCP/IP.</b><br>Female M12 circular connector, D-coded, 4-pin.<br>The instrument works in an Ethernet TCP/IP network and it is accessible via web browser.   | LCBETHETCP    |
| <b>Ethernet/IP.</b><br>2x female M12 circular connectors, D-coded, 4-pin.<br>The instrument works as <i>adapter</i> in an Ethernet/IP network.  | LCBETHEIP     |
| <b>PROFINET IO.</b><br>2x female M12 circular connectors, D-coded, 4-pin.<br>The instrument works as <i>device</i> in a Profinet IO network.  | LCBPROFINETIO |
| <b>EtherCAT.</b><br>2x female M12 circular connectors, D-coded, 4-pin.<br>The instrument works as <i>slave</i> in an EtherCAT network.  | LCBETHERCAT   |
| <b>POWERLINK.</b><br>2x female M12 circular connectors, D-coded, 4-pin.<br>The instrument works as <i>slave</i> in a Powerlink network.   | LCBPOWERLINK  |
| <b>SERCOS III.</b><br>2x female M12 circular connectors, D-coded, 4-pin.<br>The instrument works as <i>slave</i> in a Sercos III network.   | LCBSERCOSIII  |

### MAIN FUNCTIONS

- Connections to:
  - PLC via analog output or fieldbuses;
  - PC/PLC via RS485 (up to 99 instruments with line repeaters, up to 32 without line repeaters);
  - up to 4 load cells in parallel by junction box.
- Digital filter to reduce the effects of weight oscillation.
- Theoretical calibration (via PC software) and real calibration (with sample weights and the possibility of weight linearization up to 5 points).
- Tare weight zero setting.
- Automatic zero setting at power-on.
- Gross weight zero tracking.
- Semi-automatic tare (net/gross weight) and preset tare.
- Semi-automatic zero.
- Direct connection between RS485 and RS232 without converter.
- Configuration backup and restore via PC software.
- **TCP/IP WEB APP**  
Integrated software in combination with the Ethernet TCP/IP version for remote supervision, management and control of the instrument.

### COMING SOON

#### CE-M version: 2014/31/EU-EN45501:2015-OIML R76:2006

- System parameters management protected by qualified access via software (password), hardware or fieldbus.
- Weight subdivisions displaying (1/10 e) via PC software.
- Three operation mode: single interval or multiple ranges or multi-interval.
- Net weight zero tracking.
- Calibration.
- Alibi memory (option on request).

#### BASE PROGRAM

- Hysteresis and setpoint value setting.



#### SINGLE PRODUCT LOADING PROGRAM

- 99 settable formulas.
- Automatic fall calculation.
- Tolerance error control.
- Precision batching through slow function.
- Precision batching through tapping function.
- Consumption storage.
- Batching start via external contact or fieldbus.

### TECHNICAL FEATURES

|  |  |
|--|--|
| Power supply and consumption                                     | 12÷24 VDC ±10%; 5 W                            |
| Number of load cells • Load cells supply                         | up to 4 (350 Ω) - 4/6 wires • 3.3 VDC/40 mA    |
| Linearity • Analog output linearity                              | <0.01% full scale • <0.01% full scale          |
| Thermal drift • Analog output thermal drift                      | <0.0005% full scale/°C • <0.003% full scale/°C |
| A/D Converter  | 24 bit (16000000 points) - 4.8 kHz             |
| Divisions (with measurement range ±10 mV and sensitivity 2 mV/V) | ±999999 • 6.6 nV/d                             |
| Measurement range  | ±26 mV   |
| Usable load cells sensitivity                                    | ±7 mV/V  |
| Conversions per second   | 600/s  |
| Decimals • Display increments                                    | 0÷4 • x1 x2 x5 x10 x20 x50 x100                |
| Digital filter • Readings per second                             | 10 levels • 5÷600 Hz                           |
| Relay outputs  | 3 - max 115 VAC/150 mA - 24 VDC/200 mA         |
| Digital inputs   | 2 - 5÷24 VDC                                   |
| Micro USB port   | B type - USB 2.0 (full-speed)                  |
| Humidity (condensate free)                                       | 85%  |
| Storage temperature  | -30°C +80°C                                    |
| Working temperature  | -20°C +50°C                                    |

### OPTIONS ON REQUEST

|   | DESCRIPTION             | CODE      |
|---|-------------------------|-----------|
|  | Load cell + LCB wiring. | LCBCOL    |
|  | Alibi memory.           | OPZWALIBI |

The Company reserves the right to make changes to the technical data, drawings and images without notice.